

Thema: Projekt G6 - unterstützte DSP301/402-Parameter

Diese Info beschreibt die G6 unterstützten DSP301/402-Parameter.

DSP301 Adr	Objektyp	Datentyp	Attr.	SDO Sub- index	Kodierung	DSP301 Name	Combivis vorhanden
1000h	var	Uint32	ro	0		DeviceType	nein
1001h	var	Uint8	ro	0		ErrorRegister	nein
1018h	array	Uint8	ro	0		Identity object	nein
		Uint32	ro	1	14h(KEB)	VendorID	nein
		Uint32	ro	2	300000h Combivert G6 Standard	ProductCode	nein
		Uint32	ro	3	HighWord OperatorID LowWord PUApplicationID	RevisionNumber	nein
		Uint32	ro	4	xx	KEB_DeviceSerialNumber	nein
1600h	array	Uint8	rw	0	Nr of mapped objects	receive RDO mapping parameter	nein
		Uint32	rw	1	Index / Subindex / Bitlength		nein
		Uint32	rw	2	Index / Subindex / Bitlength		nein
		Uint32	rw	3	Index / Subindex / Bitlength		nein
		Uint32	rw	4	Index / Subindex / Bitlength		nein
		Uint32	rw	5	Index / Subindex / Bitlength		nein
		Uint32	rw	6	Index / Subindex / Bitlength		nein
		Uint32	rw	7	Index / Subindex / Bitlength		nein
		Uint32	rw	8	Index / Subindex / Bitlength		nein
1A00h	array	Uint8	rw	0	Nr of mapped objects	transmit PDO mapping parameter	nein
		Uint32	rw	1	Index / Subindex / Bitlength		nein
		Uint32	rw	2	Index / Subindex / Bitlength		nein
		Uint32	rw	3	Index / Subindex / Bitlength		nein
		Uint32	rw	4	Index / Subindex / Bitlength		nein
		Uint32	rw	5	Index / Subindex / Bitlength		nein
		Uint32	rw	6	Index / Subindex / Bitlength		nein
		Uint32	rw	7	Index / Subindex / Bitlength		nein
		Uint32	rw	8	Index / Subindex / Bitlength		nein
1C00h	array	Uint8	ro	0 - 4		SyncManager- ComType	nein
1C10h	array	Uint16	ro	0	0		nein
1C11h	array	Uint16	ro	0	0		nein
1C12h	array	Uint16	ro	0	1600h		nein
1C13h	array	Uint16	ro	0	1a00h		nein



Karl E. Brinkmann GmbH

Försterweg 36-38 • D-32683 Barntrop

fon: +49 5263 401-0 • fax: +49 5263 401-116

net: www.keb.de • mail: info@keb.de

© KEB	
Dokument	0400-0006
Sprache	DEU
Datum	02-2016